



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## MPSA28

### Silicon NPN Transistor

### Darlington, General Purpose Amplifier,

### TO-92 Type Package

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ , Note 1 unless otherwise specified)

Collector–Emitter Voltage, $V_{CES}$ .....	80V
Collector–Base Voltage, $V_{CBO}$ .....	80V
Emitter–Base Voltage, $V_{EBO}$ .....	12V
Continuous Collector Current, $I_C$ .....	800mA
Total Device Dissipation ( $T_A = +25^\circ\text{C}$ ), $P_D$ .....	625mW
Derate Above $25^\circ\text{C}$ .....	5mW/ $^\circ\text{C}$
Operating Junction Temperature Range, $T_J$ .....	$-55^\circ$ to $+150^\circ\text{C}$
Storage Temperature Range, $T_{stg}$ .....	$-55^\circ$ to $+150^\circ\text{C}$
Thermal Resistance, Junction–to–Case, $R_{thJC}$ .....	83.3 $^\circ\text{C}/\text{W}$
Thermal Resistance, Junction–to–Ambient, $R_{thJA}$ .....	200 $^\circ\text{C}/\text{W}$

Note 1. These ratings are limiting values above which the serviceability of any semiconductor device may be impaired. These are steady state limits and based on a maximum junction temperature of  $+150^\circ\text{C}$ .

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
<b>OFF Characteristics</b>						
Collector–Emitter Breakdown Voltage	$V_{(BR)CES}$	$I_C = 100\mu\text{A}$ , $V_{BE} = 0$	80	–	–	V
Collector–Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C = 100\mu\text{A}$ , $I_E = 0$	80	–	–	V
Emitter–Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E = 10\mu\text{A}$ , $I_C = 0$	12	–	–	V
Collector Cutoff Current	$I_{CBO}$	$V_{CB} = 60\text{V}$ , $I_E = 0$	–	–	100	nA
	$I_{CES}$	$V_{CE} = 60\text{V}$ , $V_{BE} = 0$	–	–	500	nA
Emitter Cutoff Current	$I_{EBO}$	$V_{EB} = 10\text{V}$ , $I_C = 0$	–	–	100	nA
<b>ON Characteristics (Note 2)</b>						
DC Current Gain	$h_{FE}$	$I_C = 10\text{mA}$ , $V_{CE} = 5\text{V}$	10,000	–	–	
		$I_C = 100\text{mA}$ , $V_{CE} = 5\text{V}$	10,000	–	–	
Collector–Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = 10\text{mA}$ , $I_B = 0.01\text{mA}$	–	–	1.2	V
		$I_C = 100\text{mA}$ , $I_B = 0.1\text{mA}$	–	–	1.5	V
Base–Emitter ON Voltage	$V_{BE(on)}$	$I_C = 100\text{mA}$ , $V_{CE} = 5\text{V}$	–	–	2.0	V
<b>Small Signal Characteristics</b>						
Current Gain – Bandwidth Product	$f_T$	$I_C = 10\text{mA}$ , $V_{CE} = 5\text{V}$ , $f = 100\text{MHz}$	125	–	–	MHz
Output Capacitance	$C_{obo}$	$V_{CB} = 1\text{V}$ , $I_E = 0$ , $f = 1\text{MHz}$	–	–	8	pF

Note 2. Pulse Test: Pulse Width  $\leq 300\mu\text{s}$ , Duty Cycle  $\leq 2\%$

