


## N-CHANNEL ENHANCEMENT MODE VERTICAL DMOS FET

# ZVN0540A

ISSUE 2 – MARCH 94

### FEATURES

- \* 400 Volt  $V_{DS}$
- \*  $R_{DS(on)}=50\Omega$



E-Line  
TO92 Compatible

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Drain-Source Voltage	$V_{DS}$	400	V
Continuous Drain Current at $T_{amb}=25^{\circ}\text{C}$	$I_D$	90	mA
Pulsed Drain Current	$I_{DM}$	600	mA
Gate-Source Voltage	$V_{GS}$	$\pm 20$	V
Power Dissipation at $T_{amb}=25^{\circ}\text{C}$	$P_{tot}$	700	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}\text{C}$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Drain-Source Breakdown Voltage	$BV_{DSS}$	400		V	$I_D=1\text{mA}, V_{GS}=0\text{V}$
Gate-Source Threshold Voltage	$V_{GS(th)}$	1	3	V	$I_D=1\text{mA}, V_{DS}=V_{GS}$
Gate-Body Leakage	$I_{GSS}$		20	nA	$V_{GS}=\pm 20\text{V}, V_{DS}=0\text{V}$
Zero Gate Voltage Drain Current	$I_{DSS}$		10 400	$\mu\text{A}$ $\mu\text{A}$	$V_{DS}=400\text{V}, V_{GS}=0$ $V_{DS}=320\text{V}, V_{GS}=0\text{V}, T=125^{\circ}\text{C}(2)$
On-State Drain Current(1)	$I_{D(on)}$	150		mA	$V_{DS}=25\text{V}, V_{GS}=10\text{V}$
Static Drain-Source On-State Resistance (1)	$R_{DS(on)}$		50	$\Omega$	$V_{GS}=10\text{V}, I_D=100\text{mA}$
Forward Transconductance(1)(2)gfs		100		mS	$V_{DS}=25\text{V}, I_D=100\text{mA}$
Input Capacitance (2)	$C_{iss}$		70	pF	
Common Source Output Capacitance (2)	$C_{oss}$		10	pF	$V_{DS}=25\text{V}, V_{GS}=0\text{V}, f=1\text{MHz}$
Reverse Transfer Capacitance (2)	$C_{rss}$		4	pF	
Turn-On Delay Time (2)(3)	$t_{d(on)}$		7	ns	
Rise Time (2)(3)	$t_r$		7	ns	$V_{DD}=25\text{V}, I_D=100\text{mA}$
Turn-Off Delay Time (2)(3)	$t_{d(off)}$		16	ns	
Fall Time (2)(3)	$t_f$		10	ns	

3-356

1